

# SmartLogger1000



## Smart

- Modbus-TCP for connections to Huawei NetEco
- IEC60870-5-104 for connections to third-party monitoring systems
- USB and embedded web for data reading and software upgrade
- Automatically detecting facilities and mapping RS485 addresses
- Remote control of active & reactive power

## Simple

- Up to 80 inverters per SmartLogger1000
- Up to 30 devices per RS485 bus
- Easy to install on walls, tabletops and DIN rails

## Reliable

- Max. reliable communication range of 1,000 m

Technical Specifications	SmartLogger1000
	<b>Device Management</b>
Max. Number of Manageable Devices	80
Max. Number of Manageable Smart Inverters	80
	<b>Communication Interface</b>
Electrical Ethernet	ETH x 1, 10 / 100 Mbps
RS485	COM x 3, 2400 / 4800 / 9600 / 19200 / 115200 bps
Digital / Analog Input / Output	DI x 4, DO x 3, AI x 2
	<b>Communication Protocol</b>
Ethernet	Modbus-TCP, IEC 60870-5-104
RS485	Modbus-RTU, IEC 60870-5-103 (standard), DL / T645
	<b>Interaction</b>
LCD	3.5 inch Graphic LCD
LED	LED Indicator x 3
WEB	Embedded WEB
USB	USB 2.0 x 1
	<b>Environment</b>
Operating Temperature Range	-20°C ~ 60°C (-4°F ~ 140°F)
Relative Humidity (Non-condensing)	5% ~ 95%
Max. Operating Altitude	4,000 m (13,123 ft.)
	<b>Electrical</b>
Power Supply	100 V ~ 240 V, 50 Hz / 60 Hz
Power Consumption	Typical 3 W, Max. 7 W
	<b>Mechanical</b>
Dimensions (W x H x D)	225 x 140 x 50 mm (8.9 x 5.5 x 2.0 inch)
Weight	0.5 kg (1.1 lb.)
Protection Degree	IP20
Installation Options	Wall Mounting, DIN Rail Mounting, Tabletop Mounting

The text and figures reflect the current technical state at the time of printing. Subject to technical changes. Errors and omissions excepted. Huawei assumes no liability for mistakes or printing errors. For more information, please visit solar.huawei.com. Version No.:01-(201812)

